



Gk310

GPS Personal Tracker

- ▶ **SOS call & Speed-dial**
Thumb sized button allowing urgent call during an emergency case
- ▶ **Two-way talk**
With MIC and speaker, it realizes two-way communication
- ▶ **Listen-in**
Send comand to the device and you can hear the live voice around it
- ▶ **4G LTE/WCDMA/GSM network**
4G full network coverage enables faster speed, saving your time and money
- ▶ **GPS+LBS positioning**
Allow the location to be pinpointed accurately and rapidly
- ▶ **HD touch screen**
Clearly show detailed information; more practical and useful

Gsm specifications

WCDMA	850/900/1800/2100MHz
GSM frequency	850/900/1800/1900MHz
GPRS	Class 12, TCP/IP
Memory	512MB RAM+8GB ROM
Phase error	RMSPE<5,PPE<20
Max output	GSM850/GSM900:33±3dBm, GSM1800/GSM1900:30±3dBm
Max frequency error	±0.1ppm

Gps specifications

GPS chipset	Mt6737
Frequency	L1,1575.42MHz C/A code
GPS channel	66
Location accuracy	<10 meters
Tracking sensitivity	-165dBm
Acquisition sensitivity	-148dBm
TTF (open sky)	Avg. hot start ≤1secAvg. cold start ≤35sec

Function & package

Touch screen	1.54 inch
Resolution	240*240
Battery	3.8V/1500mAh lithium-polymer battery
Max output	≥72 hours (LTE & WIFI work; GPS sleeps),>8 hours (LTE & GPS work)
Operating temperature	-20°C ~60°C
Standby current	≤14mA (LTE works while GPS sleep)
Weight	81g
Dimension	101.0 x 62.0x 11.0mm
LED	Status LED
SIM card	nano
Charger voltage/current	5VDC/1000mA
Speaker	√
Charge port	USB type-C
MIC	√

Add.:509, 5th Floor, Fortune Square-II, Daman Road, Landmark TBZ, Chala, Vapi - 396191, Gujarat.

 98252 49766 | 98257 49766 | 89800 17818

Ahemdabad | **B**angalore | **C**hennai | **D**aman | **M**umbai | **N**agpur
7069034346 | 76195 63284 | 8980014344 | 9724375577 | 7069034348 | 9561111233