

Qbit Mini GPS Tracker

- GPS + WiFi positioning**
 Allow the location to be pinpointed in real time or periodically
- IPX5 waterproof**
 Water-resistant case to ensure stable operation in tough environment
- SOS call & Speed-dial**
 Thumb sized button allowing urgent call during an emergency case
- Geo-fence alarm**
 Create geofences of any size and shape for key locations
- Voice monitoring**
 Listen to the surroundings by sending the text message
- Two-way audio**
 With MIC and speaker, it realizes two-way communication
- Low battery alarm**
 A warning will be sent by Email or SMS when low battery occurs
- Tracked by: SMS, APP, Web**
 Report location in real time through different interfaces


Application



Personal security



Sports & activities



Valuables

Gsm specifications

GSM frequency	GSM 900/1800MHz
GPRS	Class 12, TCP/IP
Memory	64 Mb
Phase error	RMSPE<5,PPE<20
Max output	GSM850/GSM900:33±3dBm, GSM1800/GSM1900:30±3dBm
Max frequency error	±0.1ppm
Receive sensitivity	Class II RBER2%(-102dBm)

Gps specifications

GPS chipset	MTK high sensitivity chip
Frequency	BDS B1,1561.098MHz; GPS L1, 1575.42MHz
GPS channel	66
Location accuracy	<10 meters
Tracking sensitivity	-165dBm
Acquisition sensitivity	-148dBm
TTFF (open sky)	Avg. hot start ≤1secAvg. cold start ≤35sec

Function & package

Battery	500mAh/3.8V Li-Polymer battery
Voice monitoring range	≤3 meters
Button	1xSOS
Working time	3 days (WiFi positioning every 10 minute)
Calling time	2 hours
Device weight	33g
Device dimension	45.0 x 45.0x 16.0mm
LED indicator	Green/Blue/Green
Standby current	≤5mA
Charger	5VDC/1A
GSM/GPS antenna	Built-in quad band GSM antenna/18.0 x 18.0 x 2.0mm,GPS ceramic antenna

Add.:509, 5th Floor, Fortune Square-II, Daman Road, Landmark TBZ, Chala, Vapi - 396191, Gujarat.

 98252 49766 | 98257 49766 | 89800 17818

Ahemdabad | **B**angalore | **C**hennai | **D**aman | **M**umbai | **N**agpur
7069034346 | 76195 63284 | 8980014344 | 9724375577 | 7069034348 | 9561111233